



## MODELS 8550/1

### 50MHz Single Channel Pulse Function Generators

- Improved replacement to HP 8116A.
- Four instruments in one: Function, Pulse, Phase and Sweep (8550) Generators
- Popular output waveforms including sine, triangle, square, pulse and DC (8550) or ramp (8551)
- Pulse output waveforms include: normal pulse, fixed duty cycle pulse, and pulse complement
- Control input is available for pulse width modulation (PWM), AM, VCO, and FM
- Changing pulse levels in less than 6ns
- Linear transition times are independently programmable for trailing and leading edges
- Control inputs for FM, VCO, and AM modulation
- Auto calibration and built-in self diagnostics
- 30 storable, non-volatile, front panel set-ups
- Standard GPIB interface

Model 8550 is an extremely high performance programmable function generator. It provides a variety of signal waveforms to be used as test stimuli for a diversity of electronic devices. For improved immunity to RFI and EMI noise, the instrument is housed in an all-round metal case. The Model 8550 offers many features and functions. such as enhanced accuracy, eight different linear and logarithmic sweep modes, automatic phase lock loop, counted burst, and internal trigger generator. Besides its normal-continuous mode, Model 8550 offers a variety of interrupted and controlled modes.

Model 8551 is a pulse/function generator, which has performance characteristics similar to the Model 8550. In addition, this instrument offers pulse and ramp waveforms as well as their complements. Model 8551 also provides an accurate control over pulse parameters and pulse transition times. The variable rise and fall times may be independently adjusted within common ranges. Linear and logarithmic sweep functions are not available on this model. Output waveforms may be gated, triggered, or may generate a burst of pre-selected

number of cycles. The generator also provides a number of externally controlled modes, including VCO, FM, AM, and PLL.

#### **Versatility**

Taborelec generators are reliable and easy to operate. Rapid, repeatable testing is assured by the user programmed non-volatile memory. Extremely broad frequency and amplitude limits permit usefulness in a variety of complex applications. Parameters are digitally set over exceptionally wide ranges:

- Frequency - 10mHz to 50MHz
- Amplitude - 10mVp-p to 32Vp-p
- Pulse Width - 10ns to 999ms
- Pulse Transitions - 5ns to 99.9ms
- Sweep - 10mHz to 50MHz (8550)
- Phase Lock Offset - 180°

#### **Self-Calibration**

Frontpanel calibration, even by inexperienced persons, has made maintenance and troubleshooting extremely easy. Output waveform parameters are compared to internal references and are stored together with correcting factors in special tables for later use. If the self-calibration routine fails

to successfully complete, the generator produces a failure list that can be evaluated, anytime, either from the front panel or through GPIB reporting query. The self-calibration capability restores full accuracy potential - even at extreme temperatures (0-50°C).

#### **IEEE-488.2 Compatibility**

The IEEE-488 standard greatly simplifies interconnection of programmable instrumentation. It clearly defines mechanical, electrical and protocol specifications. The IEEE-488.2 standard, has significantly improved definition of data formats, status reporting, and error handling. This new standard goes further and defines a set of common commands and common queries for easy and goes further and defines a set of common commands and common queries for easy instrument interchangeability between instruments made by different manufacturers. Models 8550 and 8551 fully comply with IEEE-488.2.

# MODELS 8550/1



## 50MHz Single Channel Pulse Function Generators

### Specification

#### CONFIGURATION

**Output Channels** 1

#### STANDARD WAVEFORMS

##### Waveforms:

8550	Sine, Haversine, Haver cosine, Triangle, Square, Positive Square, Negative Square, DC
8551	Sine, Haversine, Haver cosine, Triangle, Square, Positive Pulse, Negative Pulse, Ramp

**Frequency Range:** 10mHz to 50MHz.

#### SINE

##### Total Harmonic Distortion:

10mHz to 1MHz <1%

##### Harmonic & Non-Harmonic Distortion:

	<12Vp-p	>12Vp-p
1MHz to 5MHz	<-40dB	<-30dB
5MHz to 50MHz	<-30dB	<-23dB

##### Flatness:

10mHz to 1MHz	1%
1MHz to 10MHz	2%
10MHz to 50MHz	10%

#### TRIANGLE

**Linearity:** Better than 99%, <5MHz

#### SQUARE

**Duty Cycle Range:** 1% to 80%

**Rise/Fall time:** <8ns, (<6ns typ.)

**Aberration:** <5%

#### DC (8550 Only)

**Range:** -8V to +8V, into 50 $\Omega$   
-16V to +16V, into open Z

**Resolution:** 3 digits

**Accuracy:**  $\pm$  (1% of reading +100 $\mu$ V)

#### RAMP (8551 Only)

##### Period:

Range	7.000 $\mu$ s to 99.99s
Resolution	4 digits

##### Width:

Range	5.00 $\mu$ s to 999ms
Accuracy	3%
Resolution	3 digits

**Duty Cycle Range:** 1% to 80%.

**Ramp Modes:** Positive or Negative

#### PULSE (8551 Only)

**Type:** Symmetrical Pulse, Positive Pulse, Negative Pulse and Complements

**Modes:** Single, Delayed, Double, Fixed duty cycle

#### PERIOD PARAMETERS

**Range:** 20.00ns to 99.99s

**Resolution:** 4 digits

**Accuracy / Jitter:** Same as for reference

#### PULSE WIDTH

**Range:** 10.0ns to 999ms.

**Accuracy:** 10.0ns to 99.9ns 5%  $\pm$ 2ns  
100ns to 999ms 3%

**Resolution:** 3 digits

**Duty Cycle Range:** 1% to 80%; up to 99% using the complement mode

**Ramp Modes:** Positive or Negative

#### LINEAR TRANSITION TIMES

**Range:** 8.0ns to 99.9ms, in 6 overlapping ranges.

**In-Range Span:** 100:1

**Resolution:** 10:1 3 digits

100:1 2 digits

**Accuracy:**  $\pm$ (5% + 2ns), to 99.9ns;

$\pm$ 3%, above 99.9ms

**Linearity:** 3% for transitions >100ns

#### MODULATION

##### VCO / FM

**VCO Sensitivity:** 0V to -4.7V,  $\pm$ 20% produces 1/1000 frequency change from main frequency, when main frequency is set to 9999 counts.

**FM Sensitivity:** 0V to 0.5V  $\pm$ 70mV, modulates to 1% deviation from center frequency.

**Bandwidth:** DC to 50kHz.

##### AM

**Modulation Input:** DC coupled

**Bandwidth:** DC to 1MHz

##### Modulation Depth:

100mHz to 1MHz	200%
Above 1MHz	70%

##### Sensitivity:

0V to 5Vp-p Produces 100% modulations  
0V to 10Vp-p Produces suppressed carrier amplitude modulation (SCAM)

**Envelope Distortion:** <1% (Depth < 90%, carrier frequency <1MHz, and modulation frequency <50kHz)

#### PWM (8551 Only)

**Sensitivity:** 0 to 5V,  $\pm$ 20% produces >10% pulse width change from pulse width setting

**Bandwidth:** DC to 70kHz

#### SWEEP (8550 Only)

**Type:** Linear or logarithmic  
**Time:** 10ms to 999s, NOMINAL  
**Direction:** Up or down  
**Modes:** Auto, Manual, Triggered, Gated and Burst

**Width:** Logarithmic 10 decades max.  
Linear 3 decades max.

**Sweep Steps:** Logarithmic 50 to 200 steps per decade  
Linear 2 to 1000 steps per sweep

##### Sweep Output:

Logarithmic <5 decades 1V/decade  
>5 decades 0.5V/decade

Linear 0 to +5V,  $\pm$ 5%  
**Marker Output:** +5V with no marker; drops to 0V, NOMINAL, when marker frequency is reached and remains at this level until end of sweep.

**Resolution:** Same as reference

#### PHASE LOCK LOOP (PLL)

**Operation:** Output locks automatically to the frequency and phase of the external signal

**Locking Range:** 10Hz to over 60MHz

**Reference Input:** Via TRIG/REF BNC

**Impedance:** 10K $\Omega$ ,  $\pm$ 5%

**Sensitivity:** 500mVp-p

**Max. Input Level:**  $\pm$ 20V (DC + Peak AC)

**Min. Pulse Width:** 10ns.

#### PHASE OFFSET

**Range:** -180 $^\circ$  to +180 $^\circ$ , 10Hz to 20MHz

**Resolution:** 1 $^\circ$

**Accuracy:**  $\pm$ 3 $^\circ$ , 10Hz to 100kHz

#### COMMON CHARACTERISTICS

##### FREQUENCY

**Range:** 10mHz to 50MHz

**Resolution:** 4 digits

##### ACCURACY

###### Continuous:

10mHz to 1Hz 3% of reading  
1Hz to 50MHz 0.1% of reading

**VCO/Interrupted:** 3% of reading, to 50MHz

**Jitter:** <0.1%  $\pm$  50ps

Visit our website at [www.taborelec.com](http://www.taborelec.com)

  
TABOR ELECTRONICS Inc.  
Since 1971

# MODELS 8550/1



## 50MHz Single Channel Pulse Function Generators

### Specification

#### AMPLITUDE

**Output Level:** 10mV to 16Vp-p into 50Ω  
20mV to 32Vp-p, into open Z

**Resolution:** 3 digits

**Accuracy (1 KHz):** ±2% of reading

#### OFFSET

**Range:** 0 to ±800mV or 0 to ±8V

**Resolution:** 3 digits

**Accuracy:**

±800mV	±(.5% of setting + 1% of amplitude + .2mv);
±8V	± (1% of setting + 1% of amplitude + 2mv)

#### OUTPUTS

##### MAIN OUTPUT

**Connector:** Front panel BNC

**Stand-By Mode:** Output Normal or Disabled

**Impedance:** 50Ω, ±1%

**Protection:** Protected against continuous short to case ground

##### SYNC OUTPUT

**Connector:** Front panel BNC

**Output level:** 0 to 1V, into 50Ω;  
0 to 2V, open circuit

**Rise/Fall time:** <4ns, into 50Ω

**Aberrations:** <5%

#### INPUTS

##### CONTROL INPUT

**Connector:** Front panel BNC

**Modes:** VCO, FM, AM, PMW (8551)

**Input Impedance:** 10kΩ, ±5%.

**Input Level:** ±10V

##### TRIGGER INPUT

**Connector:** Via TRIG/REF BNC

**Impedance:** 10kΩ, ±5%

**Sensitivity:** 500mVp-p

**Input Level:** ±20V

**Min. Pulse Width:** 20ns

**Slope:** Positive-going leading edge.

#### RUN MODES

**Normal:** Continuous wave form is generated

**Triggered:** Each input cycle generates a single output cycle.

**Gated:** External signal enables generator. First output cycle synchronous with active slope of triggering signal. Last cycle of output wave form always completed.

**Burst:** Preset number of cycles (1-4000) stimulated by an internal, external or manual trigger.

#### TRIGGERING CHARACTERISTICS

**Frequency:**

External	Up to 50MHz
Internal	20μs to 999s

**Start Phase offset:** -90° to +90°, to 500kHz; proportionally reduced from 500.1kHz to 50MHz

**Accuracy:** ±3°, to 500kHz

**Trigger level:** -10.0V to +10.0V

**Source:** Manual (front panel push-button), internal or external stimulate.

#### GENERAL

**Voltage Range:** 115/230VAC

**Frequency Range:** 50Hz or 60Hz

**Power Consumption:** 60W max.

**Display Type:**

Size	7 segment LED's 0.5"
Resolution	4 digits

**Interfaces:** GPIB

**Stored Set-ups:** IEEE 488.2 standard interface  
30 complete sets of front panel set-ups. Storage guaranteed for 3 years

**Dimensions:**

With Feet	315 x 102 x 395 mm (WxHxD)
Without Feet	315 x 88 x 395 mm (WxHxD)

**Weight:**

Without Package	5.5kg
Shipping Weight	7kg

**Temperature:**

Operating	0°C to 50°C
Storage	-40°C to 70°C

**Specified Accuracy:** +25°C, ±5°C

**Humidity:** 80% RH, non condensing

**Safety:** CE Marked, IEC61010-1

**Calibration:** 1 year

**Warranty (1):** 3 years standard

#### ORDERING INFORMATION

MODEL	DESCRIPTION
8550	50MHz Single Channel Function Generator
8551	50MHz Single Channel Pulse Function Generator

#### ACCESSORIES

**S-Rack Mount:** 19" Single Rack Mounting Kit

**D-Rack Mount:** 19" Dual Rack Mounting Kit

**Case Kit:** Professional Carrying Bag

**Note:** Options and Accessories must be specified at the time of your purchase.

(1) Standard warranty in India is 1 year.